

**Take Control & Save Business Lighting**  
**2014 Existing Lighting Tables**

T12 Fluorescent Lamps and Fixtures with Magnetic Ballasts							
Lamp Length	Description	Number of Lamps	Watts	Lamp Length	Description	Number of Lamps	Watts
2'	F20T12	1	28	5'	F60T12	1	100
		2	46			2	135
		3	68			1	126
		4	91				
3'	F30T12 (30watt lamps)	1	43	6'	F60T12 HO	2	170
		2	70			3	250
		3	113			4	330
		4	138			F60T12 VHO	1
	F30T12 (25watt lamps)	1	40		2		310
		2	63		F72T12	1	107
		3	103			2	145
		4	125		F72T12 HO	1	135
4'	F40T12 (40watt lamps)	1	46	2		195	
		2	92	3		265	
		3	132	4		330	
		4	184	F72T12 VHO	1	180	
	F40T12 (34watt lamps)	1	42		2	300	
		2	80		3	450	
		3	114		8'	F96T12 (75watt lamps)	1
		4	148	2			180
F48T12	1	55	F96T12 (60watt lamps)	1		83	
	2	108		2		140	
F48T12 HO	1	76	F96T12 HO (110watt lamps)	1	139		
	2	130		2	257		
	3	195		3	350		
	4	260		F96T12 HO (95watt lamps)	1	125	
F48T12 VHO	1	134	2		227		
	2	240	F96T12 VHO (215watt lamps)	1	230		
	3	450		2	475		
		3		670			
				F96T12 VHO (185watt lamps)	1	200	
					2	325	

<b>Existing/Base Incandescent Lamps</b>			
<b>Description</b>	<b>Watts</b>	<b>Description</b>	<b>Watts</b>
6 Watt	6	300 Watt	300
40 Watt	40	450 Watt	450
60 Watt	60	500 Watt	500
75 Watt	75	750 Watt	750
100 Watt	100	1000 Watt	1000
150 Watt	150	1500 Watt	1500
200 Watt	200		

<b>Existing/Base Mercury Vapor Fixtures</b>			
<b>Description</b>	<b>Watts</b>	<b>Description</b>	<b>Watts</b>
50watt – 1 lamp	75	400watt – 2 lamp	880
100watt – 1 lamp	120	500watt – 1 lamp	570
175Watt – 1 lamp	205	700Watt – 1 lamp	775
250Watt – 1 lamp	285	1,000Watt – 1 lamp	1,075
400Watt – 1 lamp	454		

<b>Existing/Base Metal Halide/High Pressure Sodium Fixtures</b>			
<b>Description</b>	<b>Watts</b>	<b>Description</b>	<b>Watts</b>
150watt – 1 lamp	187	400watt – 2 lamp	880
175watt – 1 lamp	210	1000watt – 1 lamp	1070
250Watt – 1 lamp	295	1000Watt – 2 lamp	2140
400Watt – 1 lamp	460	1,000Watt – 3 lamp	3210

<b>Existing/Base Exit Signs</b>			
<b>Description</b>	<b>Watts</b>	<b>Description</b>	<b>Watts</b>
15Watt – 2 lamp incandescent	30	20Watt – 2 lamp incandescent	40

<b>Definitions</b>		
HBF – High Ballast Factor	HPS – High Pressure Sodium	RLO – Reduced Light Output
HID – High Intensity Discharge	LEC – Light Emitting Capacitor	VHO – Very High Output
HO – High Output	LED – Light Emitting Diode	MH – Metal Halide